

## FOR LED SCREW-IN EXIT RETROFIT KIT – NXRS SERIES

### SAVE THESE INSTRUCTIONS

#### IMPORTANT SAFEGUARDS:

When using electrical equipment, always adhere to basic safety precautions including the following:

#### READ AND FOLLOW ALL SAFETY INSTRUCTIONS

1. Do not use outdoors.
2. Do not use this equipment for anything other than its intended use.
3. Do not mount near gas or electric heaters.
4. Equipment should be mounted in secure locations and at heights where it will not be subject to tampering by unauthorized personnel.
5. This equipment should be serviced by qualified personnel only.
6. Use in 120V circuits only.
7. Disconnect AC power before servicing and installation.

#### CAUTION

For use with 6-inch single or double-face, stencil-faced fixtures with white or black interiors and interior enclosure dimensions of 6-1/4" H x 9-1/2" W x 7/8" D minimum and 8-7/8" H x 13-7/16" W x 3-1/4" D maximum.

#### Not for use in:

- Exit fixtures with an EXIT legend larger than 6 inches
- Exit fixtures employing more than two (2) incandescent lamps larger than 20 watts each
- Edge-lit or fluorescent fixtures

#### INSTRUCTIONS FOR INTERMEDIATE, CANDELABRA, OR BAYONET BASES

1. Remove face(s) of existing exit fixture, and remove existing incandescent lamps.
2. Replace lamps with correct LED unit adapter (intermediate, candelabra, or bayonet type base).
3. Screw in LED units (finger tight) until they are illuminated.
4. Position LED unit so the widest part of the unit faces the EXIT letters. Turn counterclockwise until parallel with fixture face.
5. Replace the exit sign face(s).

#### IMPORTANT

LEDs must be parallel to the face of the exit fixture to ensure proper light distribution.

#### WARRANTY

Juno Lighting Group warrants that its products are free from defects in material and workmanship. Juno Lighting Group's obligation is expressly limited to repair or replacement, without charge, at Juno Lighting Group's factory after prior written return authorization has been granted. This warranty shall not apply to products which have been altered or repaired outside of Juno Lighting Group's factory. This warranty is in lieu of all other warranties, expressed or implied, and without limiting the generality of the foregoing phrase, excludes any implied warranty of merchantability. Also, there are no warranties which extend beyond the description of the product on the company's literature setting forth terms of sale.

#### Product Services Phone (888) 387-2212

1300 S. Wolf Rd • P.O. Box 5065 • Des Plaines, IL 60017-5065 • Phone: 800-323-5068 • [www.junolightinggroup.com](http://www.junolightinggroup.com)

